

ACCESS
2000iACCESS
3500iACCESS
4000iACCESS
7000i

⚙️ Algemene informatie

Type	1 fase	1 fase	1 fase	1 fase
Spanningsregelaar	INVERTER	INVERTER	INVERTER	INVERTER
Maximaal uitgangsvermogen	2 kW	3.4 kW	4 kW	7.1 kW
Continu bedrijfsvermogen (COP)	1.8 kW (3.6 kW paired)	3.2 kW (6.4 kW paired)	3.6 kW (7.2 kW paired)	6.8 kW
Maximale vermogen	8.7 A	14.7 A	17.3 A	30.8 A
AC-spanning	230 V	230 V	230 V	230 V
Frequentie	50 Hz	50 Hz	50 Hz	50 Hz

⚙️ Geluidsniveau (± 3 dB(A))

Geluidsvermogensniveau ECC (LwA)	92 dB(A)	92 dB(A)	92 dB(A)	95 dB(A)
Geluidsvermogensniveau @ 7 m	67 dB(A)	67 dB(A)	67 dB(A)	70 dB(A)

⚙️ Brandstofverbruik

Brandstof	Benzine	Benzine	Benzine	Benzine
Capaciteit brandstoftank	5 L	8 L	10 L	20 L
Looptijd (¾ van het continue vermogen)	5 h	6 h	5 h	5 h

⚙️ Afmetingen en gewicht

Afmetingen L x B x H (mm)	498 x 298 x 459	580 x 350 x 535	610 x 460 x 550	870 x 726 x 685
Afmetingen verpakking L x B x H (mm)	565 x 345 x 525	600 x 360 x 550	625 x 490 x 565	980 x 690 x 560
Netto gewicht	21.5 kg	29 kg	42 kg	105 kg
Bruto gewicht	23.5 kg	32 kg	44.5 kg	107.5 kg

⚙️ Motor



Motormodel	G80-i	G160-Vi	G225-i	R420D-Vi
Maximaal vermogen	3.5 HP	4.2 HP	5 HP	11.9 HP
Referentie standaardversie	200200004	200000009	200000007	200100008
Referentie standaardversie + DIFF	—	200000009.1	200000007.1	200100008.1

⚙️ Optionele uitrusting

Kit parallelle kabels	●	●	●	—
-----------------------	---	---	---	---

