

**POWER TOOLS®****SALE SHEET - iQMS362 CE**

iQMS362 CE - 420 mm Dry Cut Masonry Saw W/ Integrated Dust Control	
POWER REQUIREMENTS	230 V
SAW MOTOR POWER	1800 W
VAC MOTOR power	500 W
SAW WEIGHT	68 kg
ARBOR SHAPE/ BLADE SIZE	Q-Drive / 420 mm
FILTER TYPE	iQ Durabond Cartridge
CUTTING DEPTH	140 mm
RIP LENGTH	610 mm straight / 450 mm diagonal
DUST CAPACITY	18 kg
SAW DIMENSIONS (LOW POSITION)	813 mm × 1016 mm × 1092 mm
INCLUDED WITH SAW	420 mm Combination Blade, Filter, Integrated Rolling Table and Stand
RETAIL PRICE	€ 2,999.00
RECOMMENDED BUT NOT INCLUDED	
EXTENSION CORD	30 m, 3x2.5 mm <sup>2</sup>
GENERATOR	4500 Continuous Watts

## 420 MM Q-DRIVE BLADES



## KEY FEATURES

- No Water; No Dust; No Mess
- Significant time savings—Fast Setup/  
Cleanup; No special cutting area required
- No wet/stained materials
- Safer, cleaner jobsites
- TNO Rated for 8 hr Work Day Outdoors



## OPERATING TIPS

- NOT A CHOP SAW; Proper dust control requires material to be table fed.
- Ensure access to adequate power, heavy gauge extension cords, proper sized generator.
- Control material feed rate; If the saw is shaking and/or more force is required, the blade is most likely glazed and needs dressing.
- Spin the vacuum filter every 20-30 minutes of cutting time.
- Maintenance – replace vacuum filter, saw motor brushes, and rolling table louvers annually (\*\*Annual Tune-Up kit is available\*\*).
- Select a blade based on the material being cut; For pavers we recommend the “Orange” HM2 blade.

## BASIC TROUBLESHOOTING

- **The blade is hot and/or having trouble cutting:**
  - The blade is most likely glazed and or warped. Try using a dressing stone to see if performance improves. If not, replace the blade.
- **The vacuum is not controlling the dust:**
  - Is there suction at the vacuum port beneath the saw? Check to make sure that the vacuum power cord is connected.
  - Is the material being table fed or chopped? Chopping blocks the vacuum port and prevents dust capture.
  - Why do I still see some dust when cutting? iQ saws are not 100% dustless, and a minor amount of dust may be visible while cutting.
- **The saw won't start:**
  - Perform a check of the saw motor brushes to make sure that they are not worn down.
  - Check to make sure that the receptacle has power and that a circuit breaker has not been tripped. Call iQ Technical Support for further assistance in diagnosing the issue.

*Each saw is covered by a 1-Year Limited Manufacturer Warranty; For Technical Support , please call 888.274.7744*

## NEW ACCESSORIES/KITS



### **ANNUAL TUNE-UP KIT** 0362-90073-01

**Retail: € 96**

INCLUDES:  
- Replacement filter  
- Table Louver Set  
- Saw Motor Brushes (2)



### **DUST BLOCKERS** iQ3X-DB

**Retail: € 89**

USE:  
- To block the dust escaping from the holes in cored brick



### **SAW COVER** 0362-90094-01

**Retail: € 89**

USE:  
- Protects saw from weather or while traveling